



SF-7000 HD

SF-7000HD Combo DVB-S2 και DVB-T2, Υψηλής ανάλυσης 5" TFT LCD με πολύγλωσσο OSD και εύχρηστο περιβάλλον εργασίας. Υποστήριξη λειτουργίας φάσματος, οθόνη φάσματος σε πραγματικό χρόνο. Υποστήριξη τυφλής αναζήτηση, υποστήριξη εξόδου βίντεο/ήχου HDTV. Πολύ εύκολο στη χρήση με το πλήκτρο συντόμευσης. Υποστήριξη RCU. Ενσωματωμένο μεγάφωνο για αναπαραγωγή ήχου, Ενσωματωμένος βομβητής και Ενσωματωμένος φωτισμός LED.

- Frequency range T2: 170-230MHZ(VHF),470-862MHZ(UHF)
 - Signal Level T2: -82 ~-10dBm
 - Impedance T2: 75Ω
 - Demodulation Scheme T2: QPSK,16QAM,64QAM,256QAM
 - Demodulation type T2: OFDM,Fully compliant with DVB-T2 Standard
 - Bandwidth T2: 6MHZ,7MHZ,8MHZ
-
- Frequency range S2: 950MHZ~2150MHZ
 - Signal Level S2: -65~-25dBm
 - Impedance S2: 75Ω
 - Demodulation S2: QPSK,8PSK
 - Symbol Rate S2: 2~45Msps
 - Support S2: 22KHZ Tone
 - Support S2: DiSEqC 1.0/1,1/1.2
-
- Dimensions: 210x150x52mm
 - LCD Display: 5 inch
 - Operation Temperature: 0°C~+40°C
 - Audio Output: built-in loudspeaker
 - Input connector: F-Male type
 - DC power supply: DC12,6V battery
 - Power Charger Input: 100~240V@50/60Hz±10%
 - Power charger output: 14V DC 3A
 - Operating time of battery: Last for 4-5 hours(fully charged)
 - Charging Hours: 6 hour