



## **AX-101B**

Ψηφιακό πολύμετρο LCD 3,5 ψηφίων με φωτισμό.

- Measurement: AC voltage, DC voltage, DC current, resistance
  - Kind of display used: LCD 3,5 digit (1999), with a backlit
  - Sampling: 2-3x/s
  - DC voltage measuring range: 100μ...200m/20/200/500V
  - DC voltage measuring accuracy:  $\pm(0,5\% + 2 \text{ digits})$
  - AC voltage measuring range: 100m...200/500V
  - AC voltage measuring accuracy:  $\pm(1,2\% + 10 \text{ digits})$
  - DC current measuring range: 1?...2m/20m/200m/10A
  - DC current measuring accuracy:  $\pm(1\% + 2 \text{ digits})$
  - Resistance measuring range: 0,1...200/2k/20k/200k/20M/200MΩ
  - Resistance measuring accuracy:  $\pm(0,8\% + 2 \text{ digits})$
  - Diode test: yes
  - Continuity test: acoustic signal for  $R < 70\Omega$
  - Operating temperature: 0...40° C
  - Overall dimensions (W x D x H): 74 x 35 x 150mm
  - Weight with battery: 156g
  - Power supply: 1 battery 9V 6F22, set without battery
  - Measuring instrument features: square waveform generator
- shock-resistant case  
manual ranging  
low battery indicator