



AX-102

AX-102 Ψηφιακό πολύμετρο LCD με θερμομετρο και Backlight

- Manufacturer: AXIOMET
- Type of meter: digital multimeter
- Measurement: continuity, AC voltage, DC voltage, AC current, DC current, resistance, temperature
- Kind of display used: LCD (2000), with a backlight
- DC voltage measuring range: 200m/2/20/200/500/600V
- DC voltage measuring accuracy: $\pm(0,5\% + 2 \text{ digits})$
- AC voltage measuring range: 2/20/200/500/600V
- AC voltage measuring accuracy: $\pm(1\% + 10 \text{ digits})$
- DC current measuring range: 200 μ /2m/20m/200m/2/10A
- DC current measuring accuracy: $\pm(1\% + 5 \text{ digits})$
- AC current measuring range: 200 μ /2m/20m/200m/2/10A
- AC current measuring accuracy: $\pm(1,8\% + 5 \text{ digits})$
- Resistance measuring range: 200/2k/20k/200k/2M/20M Ω
- Resistance measuring accuracy: $\pm(1\% + 2 \text{ digits})$
- Temperature measuring range: -20...750°C
- Diode test: yes
- Continuity test: acoustic signal for R up to 70 Ω
- Overall dimensions (W x D x H): 70x32x144mm
- Weight with battery: 200g
- Power supply: 2 batteries 1,5V LR6 (AA), set without battery
- Conform to the norm: EN61010 600V CAT III