



MPA-060Q

Μονοφωνικός ενισχυτής με ισχύ 60W, με δυνατότητα σύνδεσης ωμικών ηχείων (8-16Ohm) αλλά και ηχείων με μετασχηματιστή προσαρμογής (100Volt). Διαθέτει 3 εισόδους μικροφώνων, εκ των οποίων η πρώτη με λειτουργία Mute. 2 εισόδους σύνδεσης CD-Player ή ραδιοκασετοφώνου. Ανεξάρτητο ρυθμιστικό σε κάθε μικρόφωνο. Διαθέτει equalizer 5 περιοχών. Ενσωματώνει γεννήτρια κουδουνιού, η οποία με το πάτημα ενός κουμπιού αναπαράγεται ο ήχος στα συνδεδεμένα ηχεία. Κατάλληλος ενισχυτής για σχολεία, εκκλησίες, αίθουσες αναγγελιών, εμπορικά καταστήματα με πολλά ηχεία οροφής, κλπ. Οι διαστάσεις του είναι: 480x323x88mm και μπορεί να τοποθετηθεί σε Rack 19". Στο πίσω μέρος διαθέτει ανεμιστήρα απαγωγής θερμότητας.

- Pre-amplifier and power assignment for public broadcasting
- Three microphone inputs, one of them is first with mute function
- Two line input which can be linked to CD player or tape player
- Independent microphone and line input level control
- 5 band graphic equalizer, main output level control
- Built-in ring generator to prompt
- Three kinds of power output modes in 100V (120V), 70V and 8~16 ohms
- Provides one line output for recording or linking to another amplifier
- Rated Output Power: 60Watt
- Output mode: 8 - 16 Ohm, 70V, 100V
- Dimensions: 480x323x88m