



MPA-700Q

Μονοφωνικός ενισχυτής 350W, 8-16 Ohm, 100V με δυνατότητα σύνδεσης ωμικών ηχείων (8-16Ohm) αλλά και ηχείων με μετασχηματιστή προσαρμογής (100V). Διαθέτει 3 εισόδους μικροφώνων, εκ των οποίων η πρώτη με λειτουργία Mute. 2 εισόδους σύνδεσης CD-Player ή ραδιοκασετοφώνου. Ανεξάρτητο ρυθμιστικό σε κάθε μικρόφωνο. Διαθέτει equalizer 5 περιοχών. Ενσωματώνει γεννήτρια κουδουνιού, η οποία με το πάτημα ενός κουμπιού αναπαράγεται ο ήχος στα συνδεδεμένα ηχεία. Κατάλληλος ενισχυτής για Σχολεία, Εκκλησίες, Αίθουσες αναγγελιών, Εμπορικά καταστήματα με πολλά ηχεία οροφής, κλπ. Μπορεί να τοποθετηθεί σε Rack 19". Στο πίσω μέρος διαθέτει ανεμιστήρα επαγωγής θερμότητας.

- Pre-amplifier and power assignment for public broadcasting.
- Three microphone inputs, one of them is first with mute function.
- Two line input which can be linked to CD player or tape player.
- Independent microphone and line input level control.
- 5 band graphic equalizer, main output level control.
- Built-in ring generator to prompt.
- Three kinds of power output modes in 100V (120V), 70V and 8~16 ohms.
- Provides one line output for recording or linking to another amplifier
- Rated Output Power: 350Watt
- Output mode: 8 - 16 Ohm, 70V, 100V
- Dimensions: 480x323x88mm