



SR-300

2.4GHz Wireless A/V sender.

- **Transmission Power:** 100mW
- **Channels:** 8/4 (2410, 2430, 2450, 2470)
- **Frequency Stability:** $\pm 100\text{KHz}$
- **Video Input Level:** 1Vp-p ($\pm 0.1\text{V}$)
- **Video Input Impedance:** 75Ω
- **Audio Input Level:** 4Vp-p@1KHz
- **Audio Input Impedance:** $>10\text{K}\Omega$
- **Supply Voltage:** 5V
- **Current Consumption:** 150mA
- **Dimensions:** 44 x 20 x 6.8 mm
- **Operating Temperature:** $-30^\circ\text{C} \sim +70^\circ\text{C}$