

Mod.

# EASY METER

# PRIME DIGITAL

by ROVER

MADE IN ITALY

## DVB-T/C/S2

OEM Welcome

## THE MOST EASY, ACCURATE AND COMPLETE COMBINED SAT, TV & CATV FIELD METER



### HD


### MPEG4



With bag

### An easy life!

All the settings, measurements and pictures in one Screen



TV Spectrum



SAT Spectrum



Service list image



DVB-S2 Constellation



DVB-T Constellation (only with T2 Version)

- ACCURATE & EASY TO USE
- DVB-S2, DVB-T, DVB-C
- FULL MPEG 2 & 4 SD & HD
- AUTOMEMORY
- AUTOQUALITY

- SPECTRUM WITH MEMORY PEAK
- ROBUST METAL HOUSING
- RAIN PROOF BAG
- LONG DURATION LI-PO BATTERIES

# Mod. **EASY METER** MAIN SPECIFICATIONS


## MEASUREMENTS & SPECTRUM ANALYSIS

- **Frequency Range:** TV 44 to 880 MHz, SAT 930 to 2.150 MHz. Level accuracy: 3 dB
- **Input Impedance:** 75 ohm (interchangeable "F" connector)
- **Power range MEAS.:** TV 10 to 100 dBµV, SAT 28 to 92 dBµV, 120 dBµV with ext. attenuator
- **Fast spectrum with MAX HOLD:** full spect. capabilities with memory peak, variable span and automatic reference level.
- **Meas:** All digital and analog measurements, see related table below
- **Quality:** Auto quality Test
- **TV Memory plan:** World Wide countries with related channels plans pre-memorized
- **SAT Memory Plan:** More than 2.000 transponders pre-memorized for world wide Satellite

## GENERAL SPECIFICATIONS

- **DC voltage at RF input:** 5 - 12 - 18 - 24 V
- **Battery:** Rechargeable Li-Po battery pack, 2/3 hour duration
- **Power supply & Battery charger:** 12 Vdc
- **USB PC Interface:** For SW upgrade and memory plan management
- **Housing:** Metal box and rain proof bag
- **Size:** H 120 x W 180 x D 65 mm (meter only)
- **Weight:** 1,2 Kg.

PRIMEDIGITAL - CROSS REFERENCE

	<b>EASY METER T2</b>	<b>EASY METER</b>	<b>SAT EXPERT</b>	<b>TV METER</b>	<b>TV EXPERT</b>	<b>T2 HD EXPERT</b>	<b>QAM EXPERT</b>
							
<b>RECEPTION STANDARD</b>							
Freq. Range MHz	47 - 2.150	47 - 2.150	930 - 2.150	47 - 880	47 - 880	47 - 880	4 - 1.000
DVB-T	●	●	-	emulated	●	●	-
DVB-T2	●	-	-	emulated	-	●	-
DVB-S2	●	●	●	-	-	-	-
DVB-C	●	●	-	emulated	emulated	●	●
DVB-C2	-	-	-	emulated	emulated	-	opt.
GB20600 China	-	-	-	emulated	-	-	-
ISDB-T	opt.	opt.	-	emulated	opt.	-	-
ATSC	-	-	-	emulated	opt.	-	opt.
DOLBY audio AC3-DD+	●	-	-	-	-	-	-
MPEG & AAC audio	●	●	-	-	-	-	-
<b>MEASURE</b>							
<b>ANALOG TV PICTURE &amp; VIDEO INPUT</b>							
MPEG 4 HD Picture	●	●	-	-	-	-	-
Analog Level	●	●	●	●	●	●	●
Analog C/N (Carrier to Noise)	-	-	-	-	-	-	●
Analog V/A (Video/Audio Ratio)	●	●	-	●	●	●	●
Digital Power	●	●	●	●	●	●	●
Full Spectrum: SAT-TV-CABLE	●	●	SAT	TV & CABLE	TV & CABLE	TV & CABLE	TV & CABLE
100 CHs TV Barscan	-	-	-	●	●	●	●
MER	●	●	emulated	emulated	●	●	●
BER	●	●	-	-	●	●	●
PER	●	● (SAT)	-	-	-	●	-
SCR	●	●	-	-	-	-	-
Constellation	●	● (SAT)	-	-	●	●	●
Noise Margin	-	-	-	emulated	●	●	●
AUTO Quality test	●	●	●	●	●	●	●
COMPASS	-	-	opt.	-	-	-	-
SATEXPERT dish alignment Function	-	-	●	-	-	-	-
<b>OTHERS</b>							
Data Logger	●	●	-	●	●	●	●
Auto Discovery	●	●	-	●	●	●	●
Auto Memory	●	●	-	●	●	●	●
Manu Memory	●	●	-	●	●	●	●
DISPLAY: Graphic Monochrome LCD	-	-	●	●	●	●	●
DISPLAY: Color TFT	●	●	-	-	-	-	-
BATTERY TYPE	LI-PO	LI-PO	●	LI-PO	LI-PO	LI-PO	LI-PO
<b>ACCESSORIES</b>							
BAG & SHOULDER STRAP	●	●	●	●	●	●	●
BATTERY CHARGER	●	●	●	with USB cable	with USB cable	with USB cable	with USB cable

N.B. = Options are only available for quantities to be agreed and must be specified upon order.